



The World's Smallest LED Solution

What if the LED Indicator could also be the emergency light source?

- XY-Fi - the world's smallest Emergency LED conversion system
- XY-Fi - so discreet you hardly know it's there
- XY-Fi - designed for unobtrusive and seamless integration for a wide range of luminaire types
- XY-Fi - small but packs a powerful punch, typically delivering greater than 6m spacing's

Key Features

- Ultra Compact
- Bezel diameter only 12mm
- Integral Status Indicator LED
- Integral and remote mounting options
- DALI & Non-AutoTest operation
- Integral Strain Relief
- Secondary optics available


Supply Options

- Articulated for remote conversion
- Separate components for integral conversion

Complete installation and dimensional information available from installation sheet. Retrofitting fluorescent luminaires, simply use the existing LED indicator aperture.

SPECIFICATION

WATTAGE 3 Watts
 DRIVE CURRENT 275mA
 LUMEN OUTPUT 77 (Typical)
 CONDUCTORS AWG28 (0.08mm²)
 WIRE LOOM 3mm outer diameter
 DIMENSIONS 26mm x 12mm Ø 10mm Ø mounting hole
 WEIGHT 20g



The XY-Fi indicates green to show 'mains healthy' and switches to full output of white light when in emergency mode.



ENVIRONMENTAL CONDITIONS

OPERATING TEMPERATURE 0°C to +45°C
 STORAGE TEMPERATURE 0°C - +80°C
 RELATIVE HUMIDITY 85% RH max
 LIFETIME min 50,000 hours
 PROTECTION RATING IP40 when installed

ELECTRICAL TESTING STANDARDS
 EN 62031 EN 62471



Order Code 9005028



Order Code 9005010

For our full range please call the sales office on 01923 200160
www.bernlite.co.uk sales@bernlite.co.uk